

LD SYSTEMS U508HHC2 SISTEMA DUAL RADIOMIC A MANO CONDENS.

599,00 € tax included

Reference: LDU508HHC2



LD SYSTEMS U508HHC2 SISTEMA DUAL RADIOMIC
A MANO CONDENS.

LD Systems U508 HHC2 - Wireless Microphone System with 2 x Condenser Handheld Microphone
Set composto da : 2 x LDU508MC trasm. a mano + 1 x LDU508R2 ricevitore diversity

Overview of frequency ranges of vocal sets:

U508 // 823 - 832 MHz + 863 - 865 MHz // six systems can be used simultaneously

CARATTERISTICHE TECNICHE :

Model name: LDU508MC

Product type: Handheld microphone transmitter

Radio frequency range: 823 - 832 and 863 - 865 MHz

Channels: 96 (8 groups of 12 channels)

Microphone type: condenser

Directional characteristic: cardioid

Audio frequency response: 60 Hz - 16 kHz

RF output: Variable (10, 30, 50 mW)

Controls: Power On/Off

Indicators: LC display

Power supply: 2 x 1.5 V AA

Operating time: up to 13 hrs., battery-dependent

Length: 252 mm

Diameter: 50 mm

Model name: LDU508R2

Product type: Dual Receiver

Type: True Diversity

Radio frequency range: 823 - 832 and 863 - 865 MHz

Channels: 2 x 96 (8 groups of 12 channels)

Antenna inputs: 2

Antenna connector: BNC

Frequency response: 30 Hz - 16 kHz

Noise suppression: Squelch

THD: S/N ratio: > 100 dB

Unbalanced audio output: 2 x XLR - 12 dBV (600 ohms) / 6.3 mm TRS - 18 dBV (3 kohms)

Controls: Power On/Off, Set, Up, Down, ASC

Indicators: OLED display, 2 x 6-segment RF (A/B), antenna active (A/B), 7-segment AF

Power supply: 12 - 18 V DC

Width: 483 mm

Height: 44 mm

Depth: 190 mm